



Specifications Ledvance LED Batten  
Linear MR Switch Aluminium White  
11W 1430lm - 840 Cool White | 60cm -  
Replaces 1x18W

[View Product](#)

## General Information

|                          |                                    |
|--------------------------|------------------------------------|
| SKU                      | 255005                             |
| EAN                      | 4099854401831                      |
| Brand                    | Ledvance                           |
| Manufacturer Name        | LN MR SWITCH 600 P 11W MS 840 LEDV |
| Any Lamp all-in warranty | 5 Years                            |
| Average Lifetime (h)     | 100000                             |

## Technical Information

|                             |                 |
|-----------------------------|-----------------|
| Technology                  | LED Integrated  |
| Replaces (Watt)             | 1x18            |
| Wattage                     | 11              |
| Voltage (V)                 | 220-240         |
| Dimmable                    | Not Dimmable    |
| Colour of Light             | White           |
| Colour Code                 | 840 Cool White  |
| Colour temperature (Kelvin) | 4000 Cool White |
| Colour Rendering (Ra)       | 80-89           |
| Light colour options        | Single Color    |
| Luminous Flux (Lumen)       | 1430            |
| Luminous Efficacy (lm/W)    | 130             |

Power factor >0.90

Length 60cm

Product Type Category LED Batten

## Fixture Information

Mounting Method Surface

Fixture Connection PI [Push-in connector]

Optical Cover Opal

IP-rating IP44

Impact Protection (IK) IK03 - 0.35 joule

Operating Temperature -20 to +45

Housing Aluminium

Colour of the Fixture White

Emergency Lighting No Emergency Unit

## Dimensions

Length (mm) 561

Width (mm) 82

Height (mm) 82

## Sensor Information

Type of sensor No Sensor

**Why Any-lamp?**



Order from the **largest lighting specialist** in Europe



**Customised** quotation



Up to **7 years warranty**



**Easy** return process